

Converting FreePBX Appliance to PBXact

Versión en Español

- You will first need to have made a purchase for the FPBX to PBXact conversion for your FreePBX Appliance system from the Sangoma Portal or a Authorized Sangoma Distributor or Partner.
 - Once this purchase has been made and confirmation the order was processed you can proceed to the steps below
- The conversion process requires your FreePBX Appliance to be on version 10.13.66-18 or newer or errors and failures will happen.
 - Review this wiki to verify your current version and update if need be before proceeding below. [FreePBX-Distro-10.13.66](#)
- SSH to your PBX and login with the root user and update the license file with the command below.
 - `fwconsole sa u`

```
[root@uc-85436011 ~]# fwconsole sa u
Updating license for 85436011
```

- The update process will install additional RPMs, and make the necessary changes to the GUI behind the scenes. The end result is a complete new PBXact system. This process takes about 3-4 minutes.
- When completed you can run the following End of Line testing and all checks should come back Passed. If you have any failed checks wait 5 minutes and run again. If you still have failed checks please open a support ticket [here](#).

```
fwconsole sa eol
```

```
Sangoma License File: PASSED
Asterisk Running: PASSED
SSH Keys Installed: PASSED
Branding Module: PASSED
Operator Panel Installed: PASSED
*****
Overall Status: PASSED
[root@localhost ~]#
```